

Normas IRAM 2476

Transformadores de Subtransmisión (Tipo A)

Relación $33.000 \pm 2 \times 2,5\%$ / 13.860 V/V

| Potencia (KVA) | Pérdidas (W) | | Ucc (%) | Dimensiones (mm) | | | | Peso (kg) |
|----------------|----------------|-----------------|---------|------------------|-------|------|--------|-----------|
| | P ₀ | P _{cc} | | Largo | Ancho | Alto | Trocha | |
| 25 | 200 | 800 | 5,0 | 1600 | 700 | 1620 | - | 720 |
| 40 | 300 | 1200 | 5,0 | 1600 | 700 | 1620 | - | 750 |
| 63 | 400 | 1800 | 5,0 | 1690 | 700 | 1770 | - | 870 |
| 100 | 420 | 2100 | 5,0 | 1700 | 700 | 1770 | - | 985 |
| 160 | 600 | 3000 | 5,0 | 1750 | 720 | 1770 | - | 1170 |
| 200 | 720 | 3600 | 5,0 | 1780 | 1000 | 1850 | 850 | 1310 |
| 250 | 850 | 4250 | 5,0 | 1800 | 1000 | 1890 | 850 | 1430 |
| 315 | 1020 | 5100 | 5,0 | 1850 | 1000 | 1890 | 850 | 1650 |
| 400 | 1160 | 5800 | 5,0 | 1920 | 1000 | 2050 | 850 | 1900 |
| 500 | 1320 | 6600 | 5,0 | 2000 | 1050 | 2250 | 850 | 2170 |
| 630 | 1600 | 8000 | 5,0 | 2150 | 1100 | 2250 | 850 | 2575 |
| 800 | 1900 | 9500 | 5,0 | 2250 | 1150 | 2300 | 850 | 3200 |
| 1000 | 2200 | 11500 | 5,0 | 2300 | 1300 | 2350 | 1000 | 3900 |
| 1250 | 2700 | 13500 | 5,0 | 2300 | 1300 | 2300 | 1000 | 4300 |
| 1600 | 3200 | 16000 | 5,0 | 2400 | 1300 | 2500 | 1000 | 5400 |
| 2000 | 3700 | 18500 | 5,0 | 2400 | 1400 | 2550 | 1000 | 5680 |

